

KAKADU[™] DECORE



INSTRUCTIONS FOR USE

JAPANESE, VIETNAMESE, THAI AND BAHASA (INDONESIAN)

PRECAUTIONS



- Switch off the machine before servicing or cleaning.
- Keep out of reach of children.
- Ensure the unit is properly earthed.
- If the supply cord is damaged, it must be replaced by the manufacturer, its service agent or similarly qualified persons to avoid a hazard.
- Ensure that operators have adequate and secure working platform, when working on the machines.
- To maintain the attractive appearance of the units, wipe down and clean as often as required. Use a cloth dampened with water and detergent or a proprietary cleaner. Do not use scouring pads or abrasives.
- A Risk Assessment for non-target species should be made prior to installation



DANGER HIGH VOLTAGE!

We suggest the unit be kept on 24 hours a day, 365 days a year as some insects are about all year round. An additional advantage is security lighting for your premises. Operational costs are minimal by comparison to most other electrical appliances.

TECHNICAL SPECIFICATIONS

VOLTAGE RANGE	220V
FREQUENCY RANGE	50-60HZ
POWER CONSUMPTION (@230V 50HZ)	50W
INGRESS PROTECTION RATING	20
CLASSIFICATION	CLASS 1
AMBIENT OPERATING TEMPERATURES	10 TO +40 °C
LED DRIVER TYPE	CONSTANT CURRENT
AREA OF COVERAGE	120m2
REPLACEMENT TUBES (2 QTY)	15WATT OR RETROFIT LED TUBES
MOUNTING METHOD	WALL MOUNTED
UNIT DIMENSIONS	W:55cm X H:33cm X D:6.5cm
WEIGHT	4.3KG

SAFETY & OPERATING INSTRUCTIONS

This appliance is not intended for use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instructions concerning use of the appliance by a person responsible for their safety.

Children should be supervised to ensure that they don't play with the appliance.

This appliance is to be kept out of reach of children.

Do not replace any electrical cords yourself. You must use a registered electrical contractor.

The unit can be hard wired, but you must use a registered electrical contractor.

Operational costs are minimal by comparison to most other electrical appliances.

UNPACKING YOUR UNIT

Each unit is carefully inspected and packed before leaving our factory. Before discarding the outer carton, examine for obvious evidence of transport damage. Remove the unit and pay particular attention to the removal of all packing materials before installing the unit.

SITING

The efficiency of the unit can be affected by the intensity of other light sources, e.g.: daylight. Therefore, the unit should be mounted where competition from other light sources is minimised. In food areas, mount the unit close to, but not directly over, exposed food or preparation surfaces (preferably to attract flies away from sensitive areas rather than towards them). Observe where the flies tend to congregate and if possible, put your flytrap in or close to that area. Site the units near where flies are likely to gain access, e.g.: doors and windows opening to the outside, especially dustbin areas. Position the trap where it can be easily reached and not over working machinery where access may be difficult or dangerous. Mount the trap in a convenient location for changing the glue board and the UV LED tubes. Mount approximately 2.0 meters above the ground.

MAINTENANCE AND CLEANING INSTRUCTIONS

CAUTION: YOU MUST SWITCH OFF POWER & UNPLUG UNIT BEFORE CLEANING COMMENCES.

You must switch off power & unplug unit before cleaning commences.

Take out light tubes and remove glue board.

Remove any dust or dirt with cloth or duster.

Clean approx. once every 3 to 6 months, depending on use.

We suggest the unit be kept on 24 hours a day 365 days a year, as some insects are about all year round.

INSTALLATION & ASSEMBLY

Mount unit approx. 2.20metres above the ground in the darkest possible area. Fixings supplied.

An additional advantage is as security lighting for your premises. Operational costs are minimal by comparison to most other electrical appliances.



REPLACING TUBES & GLUE BOARDS

You must switch off power & unplug unit before replacing any part.

GLUE BOARD - will normally retain its stickiness for at least 6 weeks. However, if there is a high level of trapped insects or high dust levels you will need to replace the glue boards much earlier. Glue Pad Part No. is SKP Yellow -10 pk".

To replace old glue board, hold at one corner and pull away protective cover.

UV BLACKLIGHT TUBES (15W) & Starters (S2) should be changed approximately once every 10-12 months to maximum effectiveness.



WE RECOMMEND THAT YOU ONLY USE GENUINE REPLACEMENTS FROM PESTWEST.

NON- GENUINE PARTS DO NOT MEET THE SAME HIGH STANDARDS AND MAY VOID YOUR WARRANTY.

Thank you for purchasing a Pestwest Quality Product. Your unit has been designed for performance, durability and reliability to ensure many years of trouble free use.

WARNING - PLEASE READ INSTRUCTION CAREFULLY

GUARANTEE

The Webtrap is guaranteed for 3 years.

Manufacturer reserves the right to vary model specifications without notice

KAKADU[™] DECORE



PestWest Electronics Ltd operates a quality management system certified to ISO 9001

PestWest[®] Australia
4 Tesla Link, Wangara, Perth ,W.A 6065
Office: +61 (8) 9302 2088
email: info@pestwest.com.au

www.pestwest.com

Confidence in
Fly Control